

Tested 110-277V PHASE/TRIAC Dimmer List

Brand	Model Number (Dimmer)	Input Voltage Range	Dimming Range	Forward phase or Reverse phase	Compatibility	Remark
LUTRON	SCL-153PR-WH	100-130V	0-100%	Forward Phase	OK	Note: Dimmers with knob/button (min. adjust dimming from 0-30%)
	DVCL-153PR-WH	100-130V	0-100%			
	DVWCL-153PH-LA	100-130V	0-100%			
	CTCL-153PDH-LA	100-130V	0-100%			
	TGCL-153PR-WH	100-130V	0-100%			
	TGCL-153PH-WH	100-130V	0-100%			
	MACL-153MH-LA	100-130V	20-100%	Forward Phase	OK	OK
	CT-600PR-IV	100-130V	0-100%			
	CT-600PR-WH	100-130V	0-100%			
	CT-103PR-WH	100-130V	0-100%			
	DV-600PR-BL	100-130V	0-100%			
	DV-600PR-WH	100-130V	0-100%			
	MIR-600M	100-130V	2-100%			
	TG-600PR-LA	100-130V	4-100%			
	TG-600PR-IV	100-130V	0-100%			
	TG-600PR-WH	100-130V	0-100%			
	TG-10PR-WH	100-130V	0-100%			
	S-600PR-WH	100-130V	0-100%			
	MRF2-6ND-120-AL	100-130V	0-100%			
	MRF2-6CL-GR	100-130V	15-100%			
	DZ6HD	100-130V	22-100%			
	PD-6WCL	100-130V	19-100%			
	PD-5NE-WH	100-130V	18-100%			
	NTLV-600-277-WH	277V	1-100%			
	ST-12P-277	277V	12-100%			
NTF-10-277	277V	1-100%				
SELV-300P	100-130V	15-100%				
MSCELV-600M	100-130V	0-100%				
MEF2-6ELV-120	100-130V	0-100%				
LEVITON	VPI06-1LZ	100-130V	15-100%	Forward Phase	OK	
	TTI06-1LZ	100-130V	1-100%			
	IPL06	100-130V	15-100%			
	DZ6HD	100-130V	17-100%			
	TBL03	100-130V	15-100%			
	6672	100-130V	20-100%			
	6602	100-130V	0-100%			
	6683	100-130V	10-100%			
LEGRAND	RHCL453PNICCV6	100-130V	6-100%	Forward Phase	OK	
	WSCL450TCCCV4	100-130V	11-100%			
	LSCL453PLACCV4	100-130V	11-100%			
CRESTRON	CLW-DELVEX-P-W-S	100-130V	11-100%	Reverse Phase	OK	